

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

NOIDA INSTITUTE OF ENGINEERING AND TECHNOLOGY, GREATER NOIDA

(An Autonomous Institute Affiliated to AKTU, Lucknow)

B.Tech

SEM: IV - THEORY EXAMINATION (2023 - 2024)

Subject: Microprocessor

Time: 3 Hours

Max. Marks: 100

General Instructions:

IMP: Verify that you have received the question paper with the correct course, code, branch etc.

1. This Question paper comprises of **three Sections -A, B, & C**. It consists of Multiple Choice Questions (MCQ's) & Subjective type questions.
2. Maximum marks for each question are indicated on right -hand side of each question.
3. Illustrate your answers with neat sketches wherever necessary.
4. Assume suitable data if necessary.
5. Preferably, write the answers in sequential order.
6. No sheet should be left blank. Any written material after a blank sheet will not be evaluated/checked.

SECTION-A

20

1. Attempt all parts:-

- 1-a. Find the content of accumulator A after the execution of XRA A. (CO1) 1
- (a) 02H
 - (b) 01H
 - (c) 00H
 - (d) A0H
- 1-b. Choose vector location of TRAP. (CO1) 1
- (a) 0024H
 - (b) 0034H
 - (c) 002CH
 - (d) 003CH
- 1-c. DAA instruction is used for. (CO2) 1
- (a) Double Add Accumulator
 - (b) Decimal Adjust Accumulator
 - (c) Decrement Accumulator
 - (d) none of above
- 1-d. Carry flag is not affected after the execution of (CO2) 1
- (a) ADD B
 - (b) SBB B
 - (c) INR B

- (d) ORA B
- 1-e. Calculate the content of A at the end of this program? (CO3) 1
STC
MVI A, 35H
ACI 26H
- (a) 5Ch
(b) 2Dh
(c) 23h
(d) 5Bh
- 1-f. Which instruction is used to add the contents of the B register to the accumulator in the 8085 microprocessor? (CO3) 1
- (a) ADD B
(b) ADC B
(c) ADI data
(d) SUB B
- 1-g. The input and output operations are respectively similar to the operations. (CO4) 1
- (a) read, read
(b) write, write
(c) read, write
(d) write, read
- 1-h. The 8085 microprocessor has two instructions for data transfer between the processor and the I/O devices. (CO4) 1
- (a) Rx & Tx
(b) DIN & DOUT
(c) IN & OUT
(d) MVI & STA
- 1-i. Find the purpose of the EU (Execution Unit) in the 8086 microprocessor? (CO5) 1
- (a) It performs address calculations.
(b) It executes instructions fetched by the BIU.
(c) It manages interrupts and exceptions.
(d) It controls the flow of data between the CPU and memory.
- 1-j. 8086 can access memory up to? (CO5) 1
- (a) 512KB
(b) 1Mb
(c) 2Mb
(d) 256KB

2. Attempt all parts:-

- 2.a. After execution of the program find the status of the carry flag. (CO1) 2
MVI A, B4H
MVI C, 4BH
ADD C
MOV C, A
INR C
HLT
- 2.b. Write instructions to load the hexadecimal numbers 65H in register C and 92H in the accumulator A , then add register C and A and display result at PORT1. (CO2) 2
- 2.c. Comment on the following (CO3) 2
a)Stack b)Subroutine
- 2.d. If the memory chip size is 1024*4 bits, how many chips are required to make up 16KByte memory? (CO4) 2
- 2.e. List the difference between 8085 & 8086 Microprocessors. (CO5) 2

SECTION-B

30

3. Answer any five of the following:-

- 3-a. Different types of Machine Cycles in 8085, also list required number of T States in each cycle. (CO1) 6
- 3-b. Differentiate between Von-neumann and Harvard architecture. (CO1) 6
- 3-c. Explain the following instructions: CALL, DAD B, XTHL, STAX B, CMP M (CO2) 6
- 3-d. Evaluate the content of A at the end of this program? Also calculate total Number of T-States. (CO2) 6
MVI A, 06H
RLC
MOV B, A
RLC
RLC
ADD B
- 3.e. List the difference between PUSH-POP and CALL-RET. (CO3) 6
- 3.f. The memory address of the last location of an 8K byte memory chip is given as FFFFH. Specify the starting address. (CO4) 6
- 3.g. Draw and explain register organization of 8086. (CO5) 6

SECTION-C

50

4. Answer any one of the following:-

- 4-a. Draw and explain the internal architecture of 8085 microprocessor.(CO1) 10
- 4-b. Elaborate the following.(CO1) 10
a) Flag Register in 8085 & Represent all flags
b) Addressing modes in 8085

5. Answer any one of the following:-

- 5-a. Explain the timing diagram during of the execution of the CALL 5025H instruction by 8085 processor with the help of neat timing diagram. (CO2) 10
- 5-b. Elaborate all Logical Operations, Also tabulate the flag status of all instructions. (CO2) 10
6. Answer any one of the following:-
- 6-a. Write an assembly language program to convert any two digit decimal number/BCD to hexadecimal/binary using 8085 instruction set. (CO3) 10
- 6-b. Do the assembly language program to count continuously in hexadecimal from FF H to 00 H in a system with 0.5 microsecond clock period. Use register C to set up a one millisecond delay between each count and display the numbers at one of the output ports. (CO3) 10
7. Answer any one of the following:-
- 7-a. Elaborate interrupts, explain different types of interrupts available in 8085, also list vectored & Non-vectored, Maskable & Non-maskable.(CO4) 10
- 7-b. Differentiate between Memory Mapped I/O and peripheral Mapped I/O in details. (CO4) 10
8. Answer any one of the following:-
- 8-a. Draw and explain the Block diagram of 8255(PPI). (CO5) 10
- 8-b. Draw the internal block diagram of 8086 microprocessor. Explain the BIU and EU.(CO5) 10

COP . JULY 2024